

Tellermate T-i^x

Technical Specification and Features Sheet

Region: United Kingdom



General Characteristics	
Dimensions	T-i ^x incl. money platform Depth: 291 mm (11.4") Width: 152 mm (6.0") Height: 166 mm (6.5")
Weight	0.9 8kg (2 lbs 2 oz) Optional Battery - 0.049 kg (1.7 oz)
Load Capacity	Maximum - 2 kg (4 lbs 6 oz) Counting resolution - 1 banknote/coin
Display	
Full Graphic LCD	77 mm x 41 mm (3.0" x 1.6") 240 x 128 pixel resolution Adjustable backlight and contrast
Power	
Power Adapter	Input to suit country of use. Output 5V AC 1.2A
Power Connection	6.5 mm reverse jack on the rear panel
Power Indication	Green LED on the lower front face illuminates on power from the mains supply.
Battery (optional)	Removable, rechargeable Li-ion Duration: Over 12 hours constant use. Charging time: 4 hours using the power supply provided

External Interfaces	
USB-A	For upgrading product firmware & currency updates
Serial <i>(optional)</i>	For connection to a Tellermate supplied printer or via integration to a PC
USB-B <i>(optional)</i>	For connection to PC for data transfer via integration
Ethernet <i>(optional)</i>	Ethernet Adaptor FCC68 cat 5, 8-way connector to network via integration
Keypad	
Standard	3 'soft key' fast access keys Navigational D pad and confirmation On/Off, Home, Clear Entry, End Count
Alpha-numeric keypad <i>(optional)</i>	Integrated alpha-numerical keypad to key in numbers and letters such as till numbers or cashier names or name of coupons etc.
Environmental Requirements	
Temperatures	Storage: -20°C to 60°C (-4°F to 140°F) Operating: 5°C to 40°C (40°F to 104°F)
Humidity	All times: 0-95% RH non-condensing
Support	
Warranty	Manufacturer's 5-years*
Services	Up to 8 years Helpline, T-Cover Packages & Repair*



Choosing the Right Model for Your Cash Counting Requirements & Processes

We offer a variety of models within our weight-based cash counter range, therefore please look at our checklist to verify you cash management requirements.

We are happy to provide you with guidelines for a suitable cash counter from our available range or offer customised software to your business needs.

Requirement Checklist

- Notes: Count loose and/or bundles?
- Coins: Loose, bagged, rolled and/or full bag check?
- Float: No float, fixed or varied?
- Connectivity: Standalone, connected to printer or PC?
- Multi-Currency: Up to 4 - £/€/\$/¥, please specify for any other currency requirement, choose from over 20.
- Count Tasks: Cashing Up, Banking, Cash Lift
- Keypad: Require an alpha-numeric keypad to key in reference numbers?
- Multi-till: Capability to save up to 150 tills before sending to a PC? (Keypad req.)

T-iX Range Explained by Hardware Features



Popular Models (UK)

- T-iX 1000-DIR**
 - 1 Language: EN
 - 1 Currency: £
 - 1 Count Task: Cashing Up
 - Coins: Loose + Bagged Full Bag function
 - Notes: Loose + Bundles* (Bank)
 - Float function
- T-iX 2000-PO**
 - 1 Language: EN
 - 4 Currencies: £/€/\$/¥
 - 2 Count Tasks: Cashing Up, Banking Preparation
 - Printer option
 - Coins: Loose + Bagged, Rolled, Full Bag function
 - Notes: Loose + Bundles* (Bank straps, sleeves)
 - Float function
- T-iX 3000-GEN**
 - 1 Language: EN
 - 1 Currency: £
 - 2 Count Tasks: Cashing Up, Banking Preparation
 - Printer option
 - PC via USB-B or Serial (integration)
 - Coins: Loose + Bagged, Full Bag function
 - Notes: Loose + Bundles* (Bank straps, sleeves)
 - Float function
- T-iX 3500-GEN**
 - 1 Language: EN
 - 1 Currency: £
 - 3 Count Tasks: Cashing Up, Banking Preparation, Cash Lift
 - Printer option
 - PC via USB-B or Serial (integration)
 - Coins: Loose + Bagged, Full Bag function
 - Notes: Loose + Bundles* (Bank straps, sleeves)
 - Float function
 - Coupons + Tokens
 - Alpha-numeric keypad
 - Non-Cash Media (Card, Cheque,...)
- T-iX 4500-GEN**
 - 1 Language: EN
 - 1 Currency: £
 - 3 Count Tasks: Cashing Up, Banking Preparation, Cash Lift
 - Printer option
 - PC via USB-B, Serial, Ethernet (integration)
 - Coins: Loose + Bagged, Full Bag function
 - Notes: Loose + Bundles* (Bank straps, sleeves)
 - Float function
 - Coupons + Tokens
 - Alpha-numeric keypad
 - Non-Cash Media (Card, Cheque,...)
- T-iX 2000-D**
 - 1 Language: EN
 - 2 Currencies: £/€
 - 1 Count Task: Cashing Up
 - Printer option
 - Coins: Loose + Bagged
 - Notes: Loose + Bundles* (Bank straps)
- T-iX 2000-SCH**
 - 1 Language: EN
 - 1 Currency: £
 - 1 Count Task: Cashing Up
 - Printer option
 - Coins: Loose + Bagged
 - Notes: Loose
 - Coupons + Tokens
- T-iX 3550-GEN**
 - See T-iX 3500
 - Multi-Till (Till Check)
- T-iX 4550-GEN**
 - See T-iX 4500
 - Multi-Till (Till Check)

Software	
Available	If you require configuration different from the above popular models, we have a variety of software available that you might find suitable. Please call 01633 637 123 to confirm your requirements and availability.
Custom	We also offer a chargeable service for programming customised software, that can include count tasks named differently or the amount of count tasks available in general, the currencies you wish to count or number of float values, languages etc.
Integration	Please contact us to verify integration requirements.
Maintenance	
Method of Cleaning	Citrus based cleaner or mild detergent solution (e.g., a weak solution of household washing up liquid diluted in tap water). Moisten a clean, soft cloth with water and use to wipe unit clean. AVOID: solvent based cleaners such as alcohol, petrol, methylated spirits, white spirit, or PCB cleaner.
Accessories & Replacement Parts	
	Mains Printer, Portable Battery Printer, T-iX Battery, T-iX Power Supply, T-iX Money Platform, Tellercups

*Specific product may be dependent on software, customer or region. Exclusions apply. The above data is subject to change for continuous product improvement purposes which may take place without prior notice and at the discretion of Tellermate Ltd.; details of which are available from the manufacturer directly.